

[MS-OCSPA]: Microsoft OCSP Administration Protocol

Intellectual Property Rights Notice for Open Specifications Documentation

- **Technical Documentation.** Microsoft publishes Open Specifications documentation for protocols, file formats, languages, standards as well as overviews of the interaction among each of these technologies.
- **Copyrights.** This documentation is covered by Microsoft copyrights. Regardless of any other terms that are contained in the terms of use for the Microsoft website that hosts this documentation, you may make copies of it in order to develop implementations of the technologies described in the Open Specifications and may distribute portions of it in your implementations using these technologies or your documentation as necessary to properly document the implementation. You may also distribute in your implementation, with or without modification, any schema, IDL's, or code samples that are included in the documentation. This permission also applies to any documents that are referenced in the Open Specifications.
- **No Trade Secrets.** Microsoft does not claim any trade secret rights in this documentation.
- **Patents.** Microsoft has patents that may cover your implementations of the technologies described in the Open Specifications. Neither this notice nor Microsoft's delivery of the documentation grants any licenses under those or any other Microsoft patents. However, a given Open Specification may be covered by Microsoft [Open Specification Promise](#) or the [Community Promise](#). If you would prefer a written license, or if the technologies described in the Open Specifications are not covered by the Open Specifications Promise or Community Promise, as applicable, patent licenses are available by contacting iplg@microsoft.com.
- **Trademarks.** The names of companies and products contained in this documentation may be covered by trademarks or similar intellectual property rights. This notice does not grant any licenses under those rights. For a list of Microsoft trademarks, visit www.microsoft.com/trademarks.
- **Fictitious Names.** The example companies, organizations, products, domain names, email addresses, logos, people, places, and events depicted in this documentation are fictitious. No association with any real company, organization, product, domain name, email address, logo, person, place, or event is intended or should be inferred.

Reservation of Rights. All other rights are reserved, and this notice does not grant any rights other than specifically described above, whether by implication, estoppel, or otherwise.

Tools. The Open Specifications do not require the use of Microsoft programming tools or programming environments in order for you to develop an implementation. If you have access to Microsoft programming tools and environments you are free to take advantage of them. Certain Open Specifications are intended for use in conjunction with publicly available standard specifications and network programming art, and assumes that the reader either is familiar with the aforementioned material or has immediate access to it.

Revision Summary

Date	Revision History	Revision Class	Comments
01/25/2008	0.1	Major	MCPP RSAT Initial Availability
03/14/2008	0.1.1	Editorial	Revised and edited the technical content.
05/16/2008	0.1.2	Editorial	Revised and edited the technical content.
06/20/2008	0.1.3	Editorial	Revised and edited the technical content.
07/25/2008	0.1.4	Editorial	Revised and edited the technical content.
08/29/2008	0.1.5	Editorial	Revised and edited the technical content.
10/24/2008	1.0	Major	Updated and revised the technical content.
12/05/2008	2.0	Major	Updated and revised the technical content.
01/16/2009	3.0	Major	Updated and revised the technical content.
02/27/2009	4.0	Major	Updated and revised the technical content.
04/10/2009	4.0.1	Editorial	Revised and edited the technical content.
05/22/2009	4.0.2	Editorial	Revised and edited the technical content.
07/02/2009	4.1	Minor	Updated the technical content.
08/14/2009	4.1.1	Editorial	Revised and edited the technical content.
09/25/2009	4.2	Minor	Updated the technical content.
11/06/2009	4.2.1	Editorial	Revised and edited the technical content.
12/18/2009	4.2.2	Editorial	Revised and edited the technical content.
01/29/2010	4.3	Minor	Updated the technical content.
03/12/2010	4.3.1	Editorial	Revised and edited the technical content.
04/23/2010	4.4	Minor	Updated the technical content.
06/04/2010	4.4.1	Editorial	Revised and edited the technical content.
07/16/2010	4.4.1	No change	No changes to the meaning, language, or formatting of the technical content.
08/27/2010	4.4.1	No change	No changes to the meaning, language, or formatting of the technical content.
10/08/2010	4.4.1	No change	No changes to the meaning, language, or formatting of the technical content.
11/19/2010	4.4.1	No change	No changes to the meaning, language, or formatting of

Date	Revision History	Revision Class	Comments
			the technical content.
01/07/2011	5.0	Major	Significantly changed the technical content.
02/11/2011	5.0	No change	No changes to the meaning, language, or formatting of the technical content.
03/25/2011	5.0	No change	No changes to the meaning, language, or formatting of the technical content.
05/06/2011	5.0	No change	No changes to the meaning, language, or formatting of the technical content.
06/17/2011	5.1	Minor	Clarified the meaning of the technical content.
09/23/2011	5.1	No change	No changes to the meaning, language, or formatting of the technical content.
12/16/2011	6.0	Major	Significantly changed the technical content.
03/30/2012	6.0	No change	No changes to the meaning, language, or formatting of the technical content.
07/12/2012	6.0	No change	No changes to the meaning, language, or formatting of the technical content.
10/25/2012	6.0	No change	No changes to the meaning, language, or formatting of the technical content.
01/31/2013	6.0	No change	No changes to the meaning, language, or formatting of the technical content.
08/08/2013	7.0	Major	Significantly changed the technical content.
11/14/2013	7.0	No change	No changes to the meaning, language, or formatting of the technical content.
02/13/2014	7.0	No change	No changes to the meaning, language, or formatting of the technical content.
05/15/2014	7.0	No change	No changes to the meaning, language, or formatting of the technical content.

Contents

1 Introduction	6
1.1 Glossary	6
1.2 References	7
1.2.1 Normative References	7
1.2.2 Informative References	8
1.3 Overview	8
1.4 Relationship to Other Protocols	9
1.5 Prerequisites/Preconditions	9
1.6 Applicability Statement	9
1.7 Versioning and Capability Negotiation	9
1.8 Vendor-Extensible Fields	9
1.9 Standards Assignments	9
2 Messages	10
2.1 Transport	10
2.2 Common Data Types	11
2.2.1 Common Structures and Data Types	11
2.2.1.1 CERTTRANSBLOB	11
2.2.1.1.1 CERTTRANSBLOB Marshaling	11
2.2.1.2 BSTR	11
2.2.1.3 VARIANT	11
3 Protocol Details	12
3.1 IOCSPAdminD Client Details	12
3.1.1 Abstract Data Model	12
3.1.2 Timers	12
3.1.3 Initialization	12
3.1.4 Message Processing Events and Sequencing Rules	12
3.1.5 Timer Events	12
3.1.6 Other Local Events	12
3.2 IOCSPAdminD Server Details	12
3.2.1 Abstract Data Model	12
3.2.1.1 RevocationConfigurationList	12
3.2.1.1.1 RevocationProviderProperties	13
3.2.1.1.2 ResponderProperties	14
3.2.1.1.3 Online Responder Permissions	15
3.2.2 Timers	15
3.2.3 Initialization	15
3.2.4 Message Processing Events and Sequencing Rules	16
3.2.4.1 IOCSPAdminD	16
3.2.4.1.1 GetOCSPProperty (Opnum 3)	16
3.2.4.1.2 SetOCSPProperty (Opnum 4)	19
3.2.4.1.3 GetCAConfigInformation (Opnum 5)	20
3.2.4.1.4 SetCAConfigInformation (Opnum 6)	24
3.2.4.1.5 GetSecurity (Opnum 7)	24
3.2.4.1.6 SetSecurity (Opnum 8)	25
3.2.4.1.7 GetSigningCertificates (Opnum 9)	25
3.2.4.1.8 GetHashAlgorithms (Opnum 10)	26
3.2.4.1.9 GetMyRoles (Opnum 11)	26
3.2.4.1.10 Ping (Opnum 12)	27

3.2.5	Timer Events	27
3.2.6	Other Local Events	27
4	Protocol Examples	28
5	Security	30
5.1	Security Considerations for Implementers	30
5.1.1	Strong Administrator Authentication	30
5.1.2	KDC Security	30
5.1.3	Administrator Console Security	30
5.1.4	Administrator Credential Issuance	30
5.1.5	Practices when Using Cryptography	30
5.1.5.1	Keeping Information Secret	30
5.1.5.2	Coding Practices	31
5.1.5.3	Security Consideration Citations	31
5.2	Index of Security Parameters	31
6	Appendix A: Full IDL	32
7	Appendix B: Product Behavior	34
8	Change Tracking	39
9	Index	40

1 Introduction

This document specifies the Microsoft OCSP Administration Protocol. The protocol consists of a set of DCOM interfaces that allow administrative tools to configure the properties of the **Online Responder**.

Sections 1.8, 2, and 3 of this specification are normative and can contain the terms MAY, SHOULD, MUST, MUST NOT, and SHOULD NOT as defined in RFC 2119. Sections 1.5 and 1.9 are also normative but cannot contain those terms. All other sections and examples in this specification are informative.

1.1 Glossary

The following terms are defined in [\[MS-GLOS\]](#):

- access control entry (ACE)**
- access control list (ACL)**
- certificate**
- certificate authority (CA)**
- certificate revocation lists (CRL)**
- certificate template**
- class identifier (CLSID)**
- cryptographic service provider (CSP)**
- Distributed Component Object Model (DCOM)**
- fully qualified domain name (FQDN) (1)**
- Interface Definition Language (IDL)**
- interface identifier (IID)**
- RPC transport**
- security descriptor**
- security principal name (SPN)**
- universally unique identifier (UUID)**

The following terms are specific to this document:

Online Certificate Status Protocol (OCSP): The protocol specified in [\[RFC2560\]](#) that enables applications to determine the (revocation) state of an identified **certificate**.

Online Responder: Same meaning as **Online Responder Service**.

Online Responder Roles: A list of administrator-defined rights or **ACLs** that define the capability of a given principal on an Online Responder. Online Responder Roles are specified in [\[CIMC-PP\]](#) section 5.2 and include administrator and enrollee.

Online Responder Service: The Microsoft implementation of an OCSP server. The **Online Responder Service** receives and processes OCSP requests from clients and has components for managing the online responder.

responder: Same meaning as **Online Responder Service**.

responder properties: The set of configuration information that specifies Online Responder request processing behavior across all revocation configurations.

revocation configuration: The set of configuration information specific to each CA for which the Online Responder is authorized to issue OCSP responses. It includes how the Online

Responder obtains an OCSP response signing key and how it obtains revocation information. See section [3.2.1.1](#) for details on all the properties of a revocation configuration.

revocation provider: The set of configuration information, within the revocation configuration, that enables the **responder** to determine the revocation status of a certificate.

MAY, SHOULD, MUST, SHOULD NOT, MUST NOT: These terms (in all caps) are used as described in [\[RFC2119\]](#). All statements of optional behavior use either MAY, SHOULD, or SHOULD NOT.

1.2 References

References to Microsoft Open Specifications documentation do not include a publishing year because links are to the latest version of the documents, which are updated frequently. References to other documents include a publishing year when one is available.

1.2.1 Normative References

We conduct frequent surveys of the normative references to assure their continued availability. If you have any issue with finding a normative reference, please contact dochelp@microsoft.com. We will assist you in finding the relevant information.

[C706] The Open Group, "DCE 1.1: Remote Procedure Call", C706, August 1997, <https://www2.opengroup.org/ogsys/catalog/c706>

[CIMC-PP] National Security Agency (NSA), "Certificate Issuing and Management Components Family of Protection Profiles", Version 1.0, October 2001, http://www.commoncriteriaportal.org/files/ppfiles/PP_CIMCPP_SL1-4_V1.0.pdf

[FIPS140] FIPS PUBS, "Security Requirements for Cryptographic Modules", FIPS PUB 140, December 2002, <http://csrc.nist.gov/publications/fips/fips140-2/fips1402.pdf>

[HOWARD] Howard, M., "Writing Secure Code", Microsoft Press, 2002, ISBN: 0735617228.

[MS-CRTD] Microsoft Corporation, "[Certificate Templates Structure](#)".

[MS-DCOM] Microsoft Corporation, "[Distributed Component Object Model \(DCOM\) Remote Protocol](#)".

[MS-DTYP] Microsoft Corporation, "[Windows Data Types](#)".

[MS-ERREF] Microsoft Corporation, "[Windows Error Codes](#)".

[MS-KILE] Microsoft Corporation, "[Kerberos Protocol Extensions](#)".

[MS-NLMP] Microsoft Corporation, "[NT LAN Manager \(NTLM\) Authentication Protocol](#)".

[MS-OAUT] Microsoft Corporation, "[OLE Automation Protocol](#)".

[MS-OCSP] Microsoft Corporation, "[Online Certificate Status Protocol \(OCSP\) Extensions](#)".

[MS-RPCE] Microsoft Corporation, "[Remote Procedure Call Protocol Extensions](#)".

[MS-WCCE] Microsoft Corporation, "[Windows Client Certificate Enrollment Protocol](#)".

[RFC2119] Bradner, S., "Key words for use in RFCs to Indicate Requirement Levels", BCP 14, RFC 2119, March 1997, <http://www.rfc-editor.org/rfc/rfc2119.txt>

- [RFC2315] Kaliski, B., "PKCS #7: Cryptographic Message Syntax Version 1.5", RFC 2315, March 1998, <http://www.ietf.org/rfc/rfc2315.txt>
- [RFC2478] Baize, E., and Pinkas, D., "The Simple and Protected GSS-API Negotiation Mechanism", RFC 2478, December 1998, <http://www.ietf.org/rfc/rfc2478.txt>
- [RFC2560] Myers, M., Ankney, R., Malpani, A., et al., "X.509 Internet Public Key Infrastructure Online Certificate Status Protocol - OCSP", RFC 2560, June 1999, <http://www.ietf.org/rfc/rfc2560.txt>
- [RFC2616] Fielding, R., Gettys, J., Mogul, J., et al., "Hypertext Transfer Protocol -- HTTP/1.1", RFC 2616, June 1999, <http://www.ietf.org/rfc/rfc2616.txt>
- [RFC2797] Myers, M., Liu, X., Schaad, J., and Weinstein, J., "Certificate Management Messages Over CMS", RFC 2797, April 2000, <http://www.ietf.org/rfc/rfc2797.txt>
- [RFC2986] Nystrom, M., and Kaliski, B., "PKCS#10: Certificate Request Syntax Specification", RFC 2986, November 2000, <http://www.ietf.org/rfc/rfc2986.txt>
- [RFC3280] Housley, R., Polk, W., Ford, W., and Solo, D., "Internet X.509 Public Key Infrastructure Certificate and Certificate Revocation List (CRL) Profile", RFC 3280, April 2002, <http://www.ietf.org/rfc/rfc3280.txt>
- [RFC4120] Neuman, C., Yu, T., Hartman, S., and Raeburn, K., "The Kerberos Network Authentication Service (V5)", RFC 4120, July 2005, <http://www.ietf.org/rfc/rfc4120.txt>

1.2.2 Informative References

- [CRYPTO] Menezes, A., Vanstone, S., and Oorschot, P., "Handbook of Applied Cryptography", 1997, <http://www.cacr.math.uwaterloo.ca/hac/>
- [MS-GLOS] Microsoft Corporation, "[Windows Protocols Master Glossary](#)".

1.3 Overview

The Microsoft OCSP Administration Protocol consists of a set of **DCOM** interfaces [\[MS-DCOM\]](#) that allows administrative tools to configure the properties of a **responder**.

A responder is a server implementation of the **Online Certificate Status Protocol (OCSP)**. A responder can be configured to provide revocation information for certificates issued by one or more **certificate authorities (CAs)** by creating a **revocation configuration** for each CA key. A responder also has properties that apply generically across all revocation configurations. These properties are sometimes referenced as "responder-wide" properties or simply **responder properties**.

Using this protocol, administrative tools may perform such functions as getting or setting responder properties, creating and removing revocation configurations, and retrieving signing certificates from a responder.

The participants in this protocol are as follows:

- Online Responder computer.
- Administrator computer: A client computer that performs remote configuration or administration tasks on the Online Responder computer.

The protocol uses the IOCSAdminD DCOM interface, which offers the 10 methods documented in the following sections. These methods allow the administrator to set and retrieve properties, set and retrieve security information, and to test whether the service is responding.

1.4 Relationship to Other Protocols

The Microsoft OCSP Administration Protocol depends on the DCOM Remote Protocol [\[MS-DCOM\]](#). Microsoft DCOM negotiates its authentication method using the Generic Security Services (GSS) API [\[RFC2478\]](#). Either NT LAN Manager (NTLM) [\[MS-NLMP\]](#), or Kerberos [\[RFC4120\]](#) and [\[MS-KILE\]](#), may be selected as the authentication method.

No other Microsoft Windows protocol directly depends on the Microsoft OCSP Administration Protocol. This protocol is designed to manage a responder that implements the OCSP [\[RFC2560\]](#).

1.5 Prerequisites/Preconditions

An Online Responder requires at least one CA **certificate** or delegated certificate, as defined in [\[RFC2560\]](#), to sign responses to certificate status requests from clients.

1.6 Applicability Statement

No higher-level protocol would benefit from using this protocol as a component. This protocol is designed to be used directly by applications and tools that require the capability to administer a responder.

1.7 Versioning and Capability Negotiation

None.

1.8 Vendor-Extensible Fields

This protocol uses responder properties as defined in section [3.2.1.2](#). Vendors can define their own custom responder properties using the SetOCSPProperty method as defined in section [3.2.4.1.2](#).

1.9 Standards Assignments

No standard assignments have been received for the Microsoft OCSP Administration Protocol described in this protocol specification.

Parameter	Value
RPC Interface UUID for IOCSAdminD	{784b693d-95f3-420b-8126-365c098659f2}

2 Messages

The following sections specify how Microsoft OCS Administration Protocol messages are transported and Microsoft OCS Administration Protocol message syntax.

2.1 Transport

The Distributed Component Object Model (DCOM) Remote Protocol [\[MS-DCOM\]](#) is used as the transport protocol.

This protocol uses DCOM to create and use DCOM object references to server objects.

Microsoft OCS Administration Protocol clients initialize a connection to the server by creating and executing a DCOM activation request. As a result of this DCOM activation, the Microsoft OCS Administration Protocol client can use the DCOM client to call the methods specified in this document. The activation process is detailed in [\[MS-DCOM\]](#) section 3.2.4.

The RPC version number for all interfaces MUST be 0.0.

[\[MS-DCOM\]](#) section 3.2.4.1 specifies the various elements that an application using DCOM passes to the DCOM client as part of the initial activation request. Below are the values that the Microsoft OCS Administration Protocol sends to the DCOM layer.

General DCOM settings:

- Server name (the application-supplied server name as specified in [\[MS-DCOM\]](#) section 3.2.4.2). The Microsoft OCS Administration Protocol client sends the name of the Microsoft OCS Administration Protocol server.
- **Class identifier (CLSID)** of the object requested. This value is 6d5ad135-1730-4f19-a4eb-3f78e7c976bb.
- **Interface identifier(s) (IID)** of interface(s) requested.
 - IOCSAdminD: 784b693d-95f3-420b-8126-365c098659f2 (see section [1.9](#)). Security settings ([\[MS-DCOM\]](#) section 3.2.4.1.1.2)
- Security provider: RPC_C_AUTHN_GSS_NEGOTIATE (9) for a remote server and RPC_C_AUTHN_DEFAULT (0xFFFFFFFF) for a server on the local machine.
- Authentication level: RPC_C_AUTHN_LEVEL_PKT_PRIVACY (6).

When the security provider has the value of RPC_C_AUTHN_GSS_NEGOTIATE, there is a negotiation between the client and server security providers that results in either NTLM, as specified in [\[MS-NLMP\]](#), or Kerberos, as specified in [\[RFC4120\]](#) and [\[MS-KILE\]](#), being used as the authentication method.

When the security provider has the value of RPC_C_AUTHN_DEFAULT, DCOM will choose an authentication method as specified in [\[MS-DCOM\]](#) section 3.2.4.2.

- Impersonation level: RPC_C_IMP_LEVEL_IMPERSONATE (3).

This means the server can use the client's security context while acting on behalf of the client, to access local resources such as files on the server.

- Authentication identity and credentials: NULL.

Passing NULL authentication identity and credentials for the security provider means that the ORPC call uses the identity and credentials of the higher-layer application.

Default values, as specified in [MS-DCOM], are used for all DCOM inputs not specified above, such as **security principal name (SPN)**, client and prototype context property buffers and their context property identifiers.

2.2 Common Data Types

In addition to RPC base types and definitions specified in [C706] and [MS-RPCE], additional data types are defined in this section.

2.2.1 Common Structures and Data Types

This section defines the structures used by the Microsoft OCSP Administration Protocol. These structures are used when using interface methods to perform various operations on the server and as part of the server's response.

2.2.1.1 CERTTRANSBLOB

The CERTTRANSBLOB type is implemented as specified in [MS-WCCE] section 2.2.2.2.

2.2.1.1.1 CERTTRANSBLOB Marshaling

Within the Microsoft OCSP Administration Protocol, the [CERTTRANSBLOB](#) is used to send a **security descriptor** from the client to the responder and to retrieve same. The marshaling of security descriptors into a CERTTRANSBLOB is documented in [MS-DTYP] section 2.4.6.

2.2.1.2 BSTR

The BSTR type is implemented as specified in [MS-OAUT] section 2.2.23.2.

2.2.1.3 VARIANT

The VARIANT type is implemented as specified in [MS-OAUT] section 2.2.29.2.

3 Protocol Details

The Microsoft OCSP Administration Protocol is a request-response protocol. The client performs a server method invocation, and the server responds with the requested data or a detailed disposition code. The primary usage of this protocol is Online Responder management. Except where specified in the following section, the protocol is a single message followed by a single reply.

3.1 IOCSPAdminD Client Details

3.1.1 Abstract Data Model

None.

3.1.2 Timers

None.

3.1.3 Initialization

Microsoft OCSP Administration Protocol is initialized by instantiation of DCOM objects.

3.1.4 Message Processing Events and Sequencing Rules

Upon receiving a reply from the server in response to a method call, the client MUST validate the return code. Return codes from all method calls are of type [HRESULT](#). If the **HRESULT** indicates success (0), the client may assume that any output parameters are present and valid. For any other return code (**HRESULT** is nonzero), the client MUST assume the method call failed. Return codes are documented in [\[MS-ERREF\]](#).

3.1.5 Timer Events

None.

3.1.6 Other Local Events

None.

3.2 IOCSPAdminD Server Details

3.2.1 Abstract Data Model

3.2.1.1 RevocationConfigurationList

The server implementing the Microsoft OCSP Administration Protocol should maintain a list of revocation configurations, each of which represents a CA certificate for which the server can provide an OCSP response. This list will be referenced as RevocationConfigurationList.

Each revocation configuration in the list has a set of properties referenced as RevocationConfigurationProperties.

Within RevocationConfigurationProperties, there is a property called "Provider" that comprises a set of properties referenced as [RevocationProviderProperties](#).

Unless a property is otherwise specified as optional in the table below, it is a required property.

Property name	Meaning
RevocationConfigurationId	A string value that uniquely identifies the revocation configuration.
CACertificate	Binary data that contains the certificate holding the CA public key corresponding to this revocation configuration. This is the key of the CA that issued the certificate whose status is being checked.
HashAlgorithmId	An optional string property whose value is the name of the hash algorithm that is used in signing the OCSP responses generated by the responder.
SigningFlags	An optional unsigned integer value that specifies flags to control the selection of the private key to be used for signing OCSP responses for this revocation configuration.
SigningCertificate	An optional binary value that contains the certificate corresponding to the private key used for signing OCSP responses for this revocation configuration.
ProviderCLSID	A string property whose value is the string representation of the class identifier (CLSID) for the revocation provider COM server that is used by this revocation configuration to check the status of a certificate.
Provider	List of revocation provider properties in section 3.2.1.1.1 .
SigningCertificateTemplate	An optional string property whose value is the common name of the certificate template [MS-CRTD] to be used by the responder (if configured) to create a certificate request for the signing certificate.
CAConfig	An optional string property whose value is the configuration string for the CA [MS-WCCE] to which the responder (if configured) submits the certificate request for the signing certificate.
LocalRevocationInformation	Optional binary value that contains the certificate revocation list (CRL) to be used for revocation checking at the responder for a particular revocation configuration.
KeySpec	The key specification indicates whether the key bound to the configuration is used for encryption or for signing content. This property is not set directly using the SetCAConfigInformation method. Rather, a SigningCertificate is assigned, and the KeySpec value returned with the GetCAConfigInformation is based on the SigningCertificate. (Optional)
CSPName	The cryptographic service provider (CSP) used by the responder to sign OCSP responses for this revocation configuration. (Optional)
ErrorCode	The status of this revocation configuration. (Optional)
ReminderDuration	The reminder duration is expressed as a percentage of the signing certificate validity period and defines the time at which the responder will notify the administrator that the signing certificate is nearing the end of its lifetime. The default value is 90, but this value can be modified. (Optional)

3.2.1.1.1 RevocationProviderProperties

The following table describes the properties for the revocation provider referenced as "Provider" in the following list and their meanings.

Property name	Meaning
CrlUrITimeOut	An optional value that represents the time-out in milliseconds that the revocation provider must wait before it times out while trying to retrieve the CRL for which it is configured.
BaseCrlUrls	An optional list of strings where each string value represents a uniform resource identifier (URI) from where a base CRL can be obtained.
DeltaCrlUrls	An optional list of strings where each string value represents a URI from where a delta CRL can be obtained.
BaseCRL	The Base CRL loaded by the revocation provider. (Optional)
DeltaCRL	The Delta CRL loaded by the revocation provider. (Optional)
RevocationErrorCode	The status of this revocation provider in terms of its ability to provide revocation information. (Optional)

3.2.1.2 ResponderProperties

Apart from revocation configuration properties, the server must also maintain a list of properties pertaining to service operation. This list is called ResponderProperties. Each property is described in the following table.

Unless a property is otherwise specified as optional in the following table, it is a required property.

Property name	Meaning
AuditFilter	An optional set of flags that identify the responder events for which the security audit is performed.
ArrayController	An optional string containing the name of the machine designated as Array controller, among the list of machines that have the Online Responder Service running with the same configuration information. <1>
ArrayMembers	An optional list of strings containing names of the machines that have the Online Responder Service running with the same configuration information. <2>
NumOfThreads	An optional integer value that specifies the maximum number of simultaneous OCSP requests [MS-OCSP] that can be served by the Online Responder Service.
MaxNumOfCacheEntries	An optional integer value that specifies the maximum number of OCSP responses [MS-OCSP] cached by the responder.
LogLevel	An optional flag that specifies the level of information that should be communicated to the system (application eventlog channel) as part of operations being performed on the service.
Debug	An optional value that specifies whether the tracing for errors on the responder is enabled or not.
EnrollPollInterval	An optional value that specifies the interval at which the responder should attempt to enroll for a signing certificate (for signing OCSP responses).
RequestFlags	An optional set of flags that controls how the OCSP requests [MS-OCSP] are

Property name	Meaning
	processed on the server.
MaxIncomingMessageSize	An optional integer value that specifies the maximum size of the OCSP request [MS-OCSP], in bytes, that is allowed to be processed on the server.
NumOfBackendConnections	An optional integer value that specifies the maximum number of connections that can be created by the web server to the responder.
RefreshRate	An optional value that specifies the interval at which the web server attempts to contact the responder to obtain the latest revocation configuration information.
MaxAge	An optional integer value that specifies the value for the HTTP max-age cache-control directive [RFC2616] as part of the OCSP response.
ISAPIDebug	An optional value that specifies whether or not the tracing for errors on the web server is enabled.

3.2.1.3 Online Responder Permissions

The responder SHOULD store a list of permissions or access rights. The possible permissions values include Read and Administer. Read is defined as providing the caller with read access to the configuration information and properties of the responder. Administer access is defined as providing the caller with read and update access to the configuration information and properties of the responder. [<3>](#)

The responder security information is configured with the SetSecurity method and is retrieved with the GetSecurity method.

The responder SHOULD enforce that the caller of any method specified in section [3.2.4](#) possesses specific permissions. [<4>](#)

3.2.2 Timers

None.

3.2.3 Initialization

Interface initialization: On startup, the responder MUST ensure that remote clients have permissions to activate and call DCOM objects. Subsequently, DCOM object and interface initialization is performed by the DCOM object exporter in response to an activation request from the DCOM client. The OCSP Administration Protocol client calls the DCOM client to initiate the activation request to the server. As a result, the DCOM server returns an object reference to the DCOM client, and the OCSP Administration Protocol client can use this client object reference to make calls to the OCSP Administration Protocol server methods specified in this document. The details of DCOM object initialization on the server, in response to client activation requests and ORPC calls, are specified in [\[MS-DCOM\]](#) sections [3.1.1.3](#), [3.1.1.5.1](#), and [3.1.1.5.4](#).

Cryptographic initialization: The responder MUST have access to the **signing certificate private keys** for each revocation configuration.

3.2.4 Message Processing Events and Sequencing Rules

3.2.4.1 IOCSAdminD

The **IOCSAdminD** interface provides an RPC interface for a client to manage an online responder.

IOCSAdminD interface inherits the IUnknown interface.

The version number for IUnknown is 1.0. The **UUID** for the **IOCSAdminD** interface is: "784b693d-95f3-420b-8126-365c098659f2". Method opnum field values start with 3; opnum values 0 through 2 represent the **IUnknown** methods: QueryInterface, AddRef, and Release methods inherited from [\[MS-DCOM\]](#).

Each method MUST NOT throw exceptions.

Methods in RPC Opnum Order

Method	Description
GetOCSPProperty	Opnum: 3
SetOCSPProperty	Opnum: 4
GetCAConfigInformation	Opnum: 5
SetCAConfigInformation	Opnum: 6
GetSecurity	Opnum: 7
SetSecurity	Opnum: 8
GetSigningCertificates	Opnum: 9
GetHashAlgorithms	Opnum: 10
GetMyRoles	Opnum: 11
Ping	Opnum: 12

3.2.4.1.1 GetOCSPProperty (Opnum 3)

This method retrieves the value of a responder property from the Online Responder Service.

```
HRESULT GetOCSPProperty(  
    [in, ref] const BSTR bstrEntryName,  
    [out, ref] VARIANT* pEntryValue  
);
```

bstrEntryName: A **BSTR** that specifies the name of the property to retrieve. The Unicode string value SHOULD be one of the values listed in [ResponderProperties](#) or one of the following values.

Property name	Meaning
CAEntries	A list of strings containing the RevocationConfigurationId corresponding to each configured revocation configuration in RevocationConfigurationList.
AllEntries	A list of all the configured properties in the list ResponderProperties and all the revocation configuration properties for all revocation configurations in RevocationConfigurationList.

pEntryValue: A pointer to a [VARIANT](#). The data returned is the value of the property referenced by *bstrEntryName*. See the following table for the processing rules that apply to the *bstrEntryName* values. Other, vendor-defined *bstrEntryName* values, not defined in the following table, MAY be used, as described in the processing rules that follow the table.

Property name	Processing rule for data returned
AuditFilter	The vt member of the VARIANT referenced by <i>pEntryValue</i> MUST be set to VT_I4, and the IVal member MUST be either 0 or a bitwise OR of the following values. Flag value – Meaning 0x00000000 – Nothing is Audited. 0x00000001 – Audit start/stop of the service. 0x00000002 – Audit changes to the revocation configurations on the responder. 0x00000004 – Audit OCSF requests received by the responder. 0x00000008 – Audit changes to the security descriptor on the responder.
ArrayController	The vt member of the VARIANT referenced by <i>pEntryValue</i> SHOULD be set to VT_BSTR, and the bstrVal member SHOULD be BSTR for the Unicode string value of the Domain Name System (DNS) name of the machine designated as Array controller for the array of responder machines.
ArrayMembers	The vt member of the VARIANT referenced by <i>pEntryValue</i> SHOULD be set to VT_ARRAY VT_BSTR, and the pArray member SHOULD reference a single dimension safearray. The number of elements of the safearray referenced by pArray SHOULD be equal to the number of machines running Online Responder Service with the same configuration information. For each machine, there SHOULD be an element in the safearray referenced by pArray containing the BSTR for Unicode string value of the FQDN (1) of the machine.
NumOfThreads	The vt member of the VARIANT referenced by <i>pEntryValue</i> MUST be set to VT_I4, and the IVal member MUST be set to the maximum number of simultaneous OCSF requests [MS-OCSF] that can be served by the Online Responder Service. <5>
MaxNumOfCacheEntries	The vt member of the VARIANT referenced by <i>pEntryValue</i> MUST be set to VT_I4, and the IVal member MUST be the maximum number of OCSF responses that can be cached by the responder.
CAEntries	The vt member of the VARIANT referenced by <i>pEntryValue</i> SHOULD be set to VT_ARRAY VT_BSTR, and the pArray member SHOULD reference a single dimension safearray. The number of elements of the safearray reference by pArray SHOULD be equal to the number

Property name	Processing rule for data returned
	of entries in RevocationConfigurationList. For each revocation configuration in RevocationConfigurationList, there SHOULD be an element containing the BSTR for the Unicode string value of the RevocationConfigurationId.
LogLevel	The vt member of the VARIANT referenced by <i>pEntryValue</i> SHOULD be set to VT_I4, and the IVal member SHOULD be set to the integer value that specifies the level of information to be communicated to the system (application eventlog channel) as part of operations being performed on the service.<6>
Debug	The vt member of the VARIANT referenced by <i>pEntryValue</i> SHOULD be set to VT_I4, and the IVal member SHOULD be an integer value that specifies whether tracing for errors on the responder is enabled or not.<7>
EnrollPollInterval	The vt member of the VARIANT referenced by <i>pEntryValue</i> SHOULD be set to VT_I4, and the IVal member SHOULD be set to the integer value that specifies the frequency (in number of hours) with which the responder will attempt to enroll for a signing certificate (for signing OCSP responses).<8>
RequestFlags	The vt member of the VARIANT referenced by <i>pEntryValue</i> SHOULD be set to VT_I4, and the IVal member SHOULD be either 0 or the following value. Flag value – Meaning 0x00000001: Responder MUST reject OCSP requests that have signatures on them.
MaxIncomingMessageSize	The vt member of the VARIANT referenced by <i>pEntryValue</i> SHOULD be set to VT_I4, and the IVal member SHOULD be set to the integer value that specifies the maximum size of the OCSP request [MS-OCSP], in bytes, that is allowed to be processed on the server.
NumOfBackendConnections	The vt member of the VARIANT referenced by <i>pEntryValue</i> SHOULD be set to VT_I4, and the IVal member SHOULD be set to the integer value that specifies the maximum number of connections that can be created by the web server to the Online Responder Service.<9>
RefreshRate	The vt member of the VARIANT referenced by <i>pEntryValue</i> SHOULD be set to VT_I4, and the IVal member SHOULD be set to the integer value that specifies the frequency (in number of milliseconds) with which the web server will attempt to contact the Online Responder Service to obtain the latest revocation configuration information.
MaxAge	The vt member of the VARIANT referenced by <i>pEntryValue</i> SHOULD be set to VT_I4, and the IVal member SHOULD be set to the integer value that specifies the value for the HTTP max-age cache-control directive [RFC2616] as part of the OCSP response.
ISAPIDebug	The vt member of the VARIANT referenced by <i>pEntryValue</i> SHOULD be set to VT_I4, and the IVal member SHOULD be set to the integer value that specifies whether the tracing for errors on the web server is enabled or not.<10>
AllEntries	The vt member of the VARIANT MUST be set to VT_ARRAY VT_VARIANT, and the pArray member MUST reference a two-

Property name	Processing rule for data returned
	dimensional safearray. The number of elements in the second dimension (signifying the number of columns) of the safearray referenced by pArray MUST be 2. The number of elements in the first dimension (signifying the number of rows) of the safearray referenced by pArray MUST be set to the sum of the number of entries in ResponderProperties and the number of entries in the RevocationConfigurationList. For each property in ResponderProperties, the first column of the row MUST be a VARIANT with vt member as VT_BSTR and the bstrVal member MUST be BSTR for the Unicode string value of the name of the property. The second column of the row MUST be a VARIANT with the value defined in this table, corresponding to the name of the property. For each revocation configuration in RevocationConfigurationList, the first column of the row MUST be a VARIANT with vt member as VT_BSTR and the bstrVal member MUST be BSTR for the Unicode string value of RevocationConfigurationId. The second column of the row MUST be a VARIANT with the value defined in section 3.2.4.1.3 .

The following additional processing rules apply:

- If the value of *bstrEntryName* is not the same as one of the values specified in the preceding list or of a vendor-defined property, or if the property with the same name is not yet configured on the responder, the server MUST fail. The error code SHOULD be 0x80070002.
- If the value of *bstrEntryName* corresponds to a vendor-defined property, the server MAY return the value as a **VARIANT** containing data of the type integer, string, date, or binary object. Otherwise, for *bstrEntryName* values that do not correspond to the previous list, the server responds as if the property were not yet configured on the responder. [<11>](#)

3.2.4.1.2 SetOCSPProperty (Opnum 4)

This method configures the value of a responder property on the server.

```
HRESULT SetOCSPProperty(
    [in, ref] const BSTR bstrEntryName,
    [in, ref] const VARIANT* pEntryValue
);
```

bstrEntryName: A [BSTR](#) that specifies the name of the property to set. The Unicode string value SHOULD be one of the property name values listed in [ResponderProperties](#).

pEntryValue: A pointer to [VARIANT](#) data.

The following processing rules apply:

1. The **vt** member of the **VARIANT** referenced by *pEntryValue* SHOULD match the type specified in section [3.2.4.1.1](#) for the property corresponding to the *bstrEntryName* value. [<12>](#)
2. If the **vt** member of the **VARIANT** referenced by *pEntryValue* is VT_EMPTY and the server has a property configured with the same name as the value of *bstrEntryName*, the server MUST delete the property identified by *bstrEntryName* and return success.

3. If the **vt** member of the VARIANT referenced by *pEntryValue* is VT_EMPTY and the server does not have a property configured with the same name as the value of *bstrEntryName*, the server MUST return an error. The error code SHOULD be 0x80070002.
4. If *bstrEntryName* matches one of the properties specified in section [3.2.1.2](#):
 1. If the server has a property configured with the same name, the server MUST replace the existing value with the value specified in the VARIANT data referenced by *pEntryValue*.
 2. If the server does not have a property configured with the same name, the server MUST store the property and value specified in the VARIANT data referenced by *pEntryValue* in its configuration.
5. If *bstrEntryName* is NULL or empty, the server SHOULD return the error E_INVALIDARG (0x8000003L).
6. If *bstrEntryName* is not empty and does not match one of the properties specified in section [3.2.1.2](#), the server SHOULD store the property and value specified in the VARIANT data referenced by *pEntryValue* in its configuration. The values "CAEntries" and "AllEntries" SHOULD NOT be used for *bstrEntryName* because of their special treatment by the GetOCSPProperty method.

3.2.4.1.3 GetCAConfigInformation (Opnum 5)

The **GetCAConfigInformation** method retrieves all the properties associated with a particular revocation configuration.

```
HRESULT GetCAConfigInformation(
    [in, ref] const BSTR bstrCAId,
    [out, ref] VARIANT* pEntryValue
);
```

bstrCAId: A [BSTR](#) that specifies the [RevocationConfigurationId](#) for the revocation configuration whose properties are to be retrieved.

pEntryValue: A pointer to a [VARIANT](#) data type that contains the names and values of all configured revocation configuration properties.

The following processing rules apply:

1. The server MUST look in the RevocationConfigurationList for the revocation configuration whose RevocationConfigurationId value is the same as the *bstrCAId* value. This is a case-insensitive lookup. If the revocation configuration is not found, then the responder MUST fail the request. The error code SHOULD be 0x800710d8.
2. Otherwise, for the revocation configuration identified by *bstrCAId*, the server MUST return the properties associated with it as the value of *pEntryValue*. The server MUST set the **vt** member of the VARIANT referenced by *pEntryValue* to VT_ARRAY | VT_VARIANT. The pArray member of the VARIANT referenced by *pEntryValue* MUST reference a two-dimensional safearray. The number of elements in the second dimension (signifying the number of columns) of the safearray referenced by pArray MUST be 2. The number of elements in the first dimension (signifying the number of rows) of the safearray referenced by pArray MUST be set to the number of properties for the revocation configuration. For each revocation configuration property, the first column of the row MUST be a VARIANT with **vt** member set to VT_BSTR, and the **bstrVal** member set to the BSTR for the Unicode

string value of the name of the property. The second column of the row MUST be a VARIANT with value defined in the following table, in the row corresponding to the name of the property.

Property name	Processing rule
CACertificate	The vt member of the VARIANT MUST be set to VT_ARRAY VT_UI1, and the pArray member MUST reference a single dimension safearray. The number of elements of the safearray reference by pArray MUST be equal to the length in bytes of the ASN.1 DER encoding of the CA certificate for which this revocation configuration is configured.
HashAlgorithmId	The vt member of the VARIANT MUST be set to VT_BSTR, and the bstrVal member MUST be the BSTR for the Unicode string value of the hash algorithm used by the responder to sign OCSP responses for this revocation configuration. <13>
SigningFlags	<p>The vt member of the VARIANT MUST be set to VT_I4, and the IVal member MUST be either 0 or a bitwise OR of the following values.</p> <p>0x00000002 - The server is configured to use the CA certificate for this revocation configuration to sign the OCSP responses.</p> <p>0x00000010 - The revocation configuration is configured to look for an OCSP certificate that has the designated OCSP signing certificate enhanced key usage in its extension (see OCSP [RFC2560]).</p> <p>0x00000020 - The revocation configuration is configured to require that an OCSP signing certificate be designated manually by setting the "SigningCertificate" property.</p> <p>0x00000004 - When a delegated signing certificate (as defined in [RFC2560]) is used for generating responses, the revocation configuration is configured to use the renewed signing certificate automatically, whenever such a certificate becomes available at the responder machine. Renewal is described in [MS-WCCE].</p> <p>0x00000040 - The responder is configured to include the signing public key hash in responses for this revocation configuration. (See [RFC2560] for OCSP server identifier details.)</p> <p>0x00000080 - The responder is configured to include the signing certificate subject in responses for this revocation configuration. (See [RFC2560] for OCSP server identifier details.)</p> <p>0x00000100 - The responder is configured to accept a nonce in the request. (See [RFC2560] nonce extensions in the OCSP request.)</p> <p>0x00000001 - For this revocation configuration, the responder is configured to silently acquire the private key associated with the signing certificate identified by the "SigningCertificate" property.</p> <p>0x00000008 - If this value is set, the responder is configured only to use signing certificates issued by the same cryptographic key as the CA for which this revocation configuration is configured.</p> <p>0x00000200 - For this revocation configuration, the responder is configured to enroll for a signing certificate from the CA defined by the property "CAConfig" using the certificate template defined by the property "SigningCertificateTemplate".</p>
SigningCertificate	The vt member of the VARIANT MUST be set to VT_ARRAY VT_UI1, and the pArray member MUST reference a single dimension safearray. The number of elements of the safearray referenced by pArray MUST be equal to the length in bytes of the ASN.1 DER

Property name	Processing rule
	encoding of the signing certificate used by the responder to sign OCSP responses for this revocation configuration.
ErrorCode	The vt member of the VARIANT MUST be set to VT_I4, and the IVal member MUST be the HRESULT DWORD value denoting the status of this revocation configuration. A value of 0 implies that this revocation configuration is properly configured with an OCSP signing certificate and that the cryptographic key pair associated with the signing certificate is accessible and ready to use for signing OCSP responses. See [MS-ERREF] for a list of the possible error codes.
CAConfig	The vt member of the VARIANT MUST be set to VT_BSTR, and the bstrVal member MUST be the BSTR for the Unicode string for the CA configuration string [MS-WCCE] to which the responder submits the certificate request for the signing certificate.
SigningCertificateTemplate	The vt member of the VARIANT MUST be set to VT_BSTR, and the bstrVal member MUST be the BSTR for the Unicode string for the common name of the certificate template [MS-CRTD] to be used by the responder to create a certificate request for signing certificate.
LocalRevocationInformation	The vt member of the VARIANT MUST be set to VT_ARRAY VT_UI1, and the pArray member MUST reference a single dimension safearray. The number of elements of the safearray reference by pArray MUST be equal to the length in bytes of the ASN.1 encoded CRL to be used for local revocation checking at the responder for a particular revocation configuration.
CSPName	The vt member of the VARIANT MUST be set to VT_BSTR, and the bstrVal member MUST be the BSTR for the Unicode string value of the cryptographic service provider (CSP) used by the responder to sign OCSP responses for this revocation configuration.
KeySpec	The vt member of the VARIANT MUST be set to VT_I4, and the IVal member MUST be the key Specification. The possible values are based on the SigningCertificate and the following rules: Flag value – Meaning 0x00000000 - The asymmetric key-pair associated with the SigningCertificate and used for signing could be either an encryption key or a signing key type. 0x00000001 - The asymmetric key-pair associated with the SigningCertificate and used for signing is an encryption key type. 0x00000002 - The asymmetric key-pair associated with the SigningCertificate and used for signing is a signing key type.
ProviderCLSID	The vt member of the VARIANT MUST be set to VT_BSTR, and the bstrVal member must be the BSTR for the Unicode string representation of CLSID for the revocation provider COM server that is used by this revocation configuration to check the status of a certificate. <14>
Provider	This is a VARIANT data type that contains the value of the properties of the revocation provider. The vt member of the VARIANT MUST be set either to VT_EMPTY or VT_ARRAY VT_VARIANT. If the vt member is set to VT_ARRAY VT_VARIANT, then the pArray

Property name	Processing rule
	member MUST reference a two-dimensional safearray. The number of elements in the second dimension (signifying the number of columns) of the safearray referenced by pArray MUST be 2. The number of elements in the first dimension (signifying the number of rows) of the safearray referenced by pArray MUST be set to the number of properties for the revocation provider. For each revocation provider property, the first column of the row MUST be a VARIANT with vt member set to VT_BSTR, and the bstrVal member set to the BSTR for the Unicode string value of the revocation provider property name. The second column of the row MUST be a VARIANT with the value defined in the following table (corresponding to the name of the revocation provider property).

The following table gives the processing rules for the revocation provider.

Property name	Processing rules
CrlUrlTimeOut	The vt member of the VARIANT MUST be set to VT_I4, and the ival member MUST be the time-out in milliseconds that the revocation provider must wait before it times out while trying to retrieve the CRL for which it is configured.
BaseCrlUrls	The vt member of the VARIANT MUST be set to VT_ARRAY VT_BSTR, and the pArray member MUST reference a single dimension safearray. The number of elements of the safearray reference by pArray MUST be equal to the number of URIs from where a base CRL [RFC3280] can be retrieved. For each URI, there MUST be an element in safearray referenced by pArray containing the BSTR for the Unicode string value of the URI.
DeltaCrlUrls	The vt member of the VARIANT MUST be set to VT_ARRAY VT_BSTR, and the pArray member MUST reference a single dimension safearray. The number of elements of the safearray reference by pArray MUST be equal to the number of URIs from where a delta CRL [RFC3280] can be retrieved. For each URI, there MUST be an element in safearray referenced by pArray containing the BSTR for the Unicode string value of the URI.
BaseCrl	The vt member of the VARIANT MUST be set to VT_ARRAY VT_UI1, and the pArray member MUST reference a single dimension safearray. The number of elements of the safearray reference by pArray MUST be equal to the length in bytes of the ASN.1 encoded binary representation of the Base CRL loaded by the revocation provider.
DeltaCrl	The vt member of the VARIANT MUST be set to VT_ARRAY VT_UI1, and the pArray member MUST reference a single dimension safearray. The number of elements of the safearray reference by pArray MUST be equal to the length in bytes of the ASN.1 encoded binary representation of the Delta CRL loaded by the revocation provider.
RevocationErrorCode	The vt member of the VARIANT MUST be set to VT_I4, and the ival member MUST be the HRESULT DWORD value denoting the status of this revocation provider. A value of 0 means that the revocation provider can provide certificate revocation status for certificates issued by the certificate authority configured for the revocation configuration. See [MS-ERREF] for a list of the possible error codes.

3.2.4.1.4 SetCAConfigInformation (Opnum 6)

This method sets all the properties for a particular revocation configuration.

```
HRESULT SetCAConfigInformation(  
    [in, ref] const BSTR bstrCAId,  
    [in, ref] const VARIANT* pEntryValue  
);
```

bstrCAId: This is a [BSTR](#) that specifies the [RevocationConfigurationId](#) for the revocation configuration whose properties are to be set.

pEntryValue: This is a pointer to a [VARIANT](#) data type that contains the names and values of the properties to set.

The following processing rules apply:

1. If *bstrCAId* is NULL or empty, the server SHOULD return the error E_INVALIDARG (0x8000003L).
2. The type of the variant as identified by *pEntryValue* MUST be either VT_EMPTY or VT_ARRAY|VT_VARIANT. If *pEntryValue* is a variant of type VT_ARRAY|VT_VARIANT, each element in this variant array SHOULD be a property identified in section [3.2.1.1](#), with the exception of the KeySpec property as noted in the table in that section. If the variant is of any other type, the responder SHOULD fail the request with an error code of 0x8000FFFF.
3. If there is a revocation configuration in the RevocationConfigurationList with the same RevocationConfigurationId as the value of *bstrCAId*, then:
 1. If *pEntryValue* is of type VT_EMPTY, the responder MUST delete the revocation configuration identified by *bstrCAId* from the RevocationConfigurationList, delete all its associated properties, and return success.
 2. If *pEntryValue* is of type VT_ARRAY|VT_VARIANT, the responder MUST delete the original revocation configuration from RevocationConfigurationList, add a new entry with the same RevocationConfigurationId, store the properties and values in the VARIANT reference by *pEntryValue* parameter, and return success.
4. If there is not a revocation configuration in the RevocationConfigurationList with the same RevocationConfigurationId as the value of *bstrCAId*, then:
 1. If *pEntryValue* is of type VT_ARRAY|VT_VARIANT, the responder MUST create a new revocation configuration in the RevocationConfigurationList, and the responder MUST store all the properties present in the *pEntryValue* parameter for the new revocation configuration. The responder MUST successfully process the request.
 2. If *pEntryValue* is of type VT_EMPTY, the responder MUST fail the request. The error code SHOULD be 0x800710d8.

3.2.4.1.5 GetSecurity (Opnum 7)

The **GetSecurity** method is used to retrieve the security descriptor associated with the responder.

```
HRESULT GetSecurity(  
    [out, ref] CERTTRANSBLOB* pctbSD
```


);

pctbSD: This is a pointer to a [CERTTRANSBLOB](#) structure that contains the marshaled Security Descriptor. Information on Security Descriptors is documented in [\[MS-DTYP\]](#) section 2.4.6. [<15>](#)

3.2.4.1.6 SetSecurity (Opnum 8)

The **SetSecurity** method is used to set the Online Responder Security, as defined in the [Abstract Data Model](#).

```
HRESULT SetSecurity(  
    [in, ref] CERTTRANSBLOB* pctbSD  
);
```

pctbSD: A pointer to the [CERTTRANSBLOB](#) structure that contains the marshaled security descriptor. Information on security descriptors is documented in [\[MS-DTYP\]](#) section 2.4.6.

The responder SHOULD use the permissions set in *pctbSD* to deny and allow operations on the responder.

3.2.4.1.7 GetSigningCertificates (Opnum 9)

The **GetSigningCertificates** method retrieves a list of certificates available at the responder machine that can be used to sign responses to OCSF requests regarding certificates issued by the CA certificate specified.

```
HRESULT GetSigningCertificates(  
    [in, ref] const VARIANT* pCAVar,  
    [out, ref] VARIANT* pSigningCertificates  
);
```

pCAVar: A pointer to a [VARIANT](#) data type containing the CA certificate. The **vt** member of **VARIANT** SHOULD be set to VT_ARRAY | VT_UI1, and the pArray member SHOULD reference a safearray that contains the ASN.1 DER encoded X.509 certificate data type containing the CA certificate.

pSigningCertificates: A pointer to **VARIANT** data type containing the list of certificates. On successful return, the server SHOULD set the vt member of the **VARIANT** to VT_ARRAY|VT_UI1, and the pArray member SHOULD reference a safearray that contains the ASN.1 DER encoded degenerate PKCS#7 [\[RFC2315\]](#) containing the certificates.

The following processing rules apply:

1. If *pCAVar* or *pSigningCertificates* is NULL, the responder MUST fail the request. The error code SHOULD be 0x800706f4.
2. The **VARIANT** referenced by *pCAVar* SHOULD have **vt** member set to VT_ARRAY | VT_UI1; otherwise, the server MUST fail the request. The error code SHOULD be 0x80070057.
3. The pArray member of the **VARIANT** referenced by *pCAVar* SHOULD reference a safearray that contains the ASN.1 DER encoded X509 certificate; otherwise, the server MUST fail the request. The error code SHOULD be 0x80070057.

4. Each certificate returned in the PKCS#7 contained in *pSigningCertificate* SHOULD meet the following criteria:
 - The certificate MUST include the extension id-kp-OCSPSigning in an extendedKeyUsage defined in [\[RFC2560\]](#) section 4.2.2.2.
 - The certificate MUST be signed by the CA certificate passed in *pCAVar* to this method.
 - The responder MUST have access to the private key corresponding to the public key in the certificate.
5. If there are no OCSP signing certificates that match the criteria specified in processing rule (4), the server SHOULD return an empty list of signing certificates as an ASN.1 DER encoded degenerate PKCS#7 [\[RFC2315\]](#) containing no certificates.

3.2.4.1.8 GetHashAlgorithms (Opnum 10)

The **GetHashAlgorithms** method retrieves the list of hash algorithms available at the responder that could be used along with the signing certificate associated with a revocation configuration to sign OCSP responses.

```
HRESULT GetHashAlgorithms(
    [in, ref] const BSTR bstrCAId,
    [out, ref] VARIANT* pHashAlgorithms
);
```

bstrCAId: A [BSTR](#) that specifies the [RevocationConfigurationId](#).

pHashAlgorithms: A pointer to a [VARIANT](#) that is of type VT_ARRAY | VT_BSTR. Each element in the array is the name of a hash algorithm that could be used along with the signing certificate associated with a revocation configuration identified by *bstrCAId* to sign OCSP responses.

The following processing rules apply:

1. If *bstrCAId* or *pHashAlgorithms* has a NULL value, the responder MUST fail the request. The error code SHOULD be 0x800706f4.
2. If a revocation configuration with same RevocationConfigurationId as the value of *bstrCAId* does not exist in the RevocationConfigurationList, the responder MUST fail the request. The error code SHOULD be 0x800710d8.
3. Otherwise, if the revocation configuration (identified) has a signing certificate property associated with it, the server SHOULD return the list of hash algorithms that can be used with the public key associated with the signing certificate to sign OCSP responses.
4. If the revocation configuration does not have a signing certificate property associated with it, the server SHOULD return a default list of hash algorithms. [<16>](#)

3.2.4.1.9 GetMyRoles (Opnum 11)

The **GetMyRoles** method retrieves the **Online Responder Roles** [\[CIMC-PP\]](#) assigned to the user that calls the method.

```
HRESULT GetMyRoles(
```

```
[out] LONG* pdwRoles  
);
```

pdwRoles: Reference to an unsigned integer value that represents the retrieved Online Responder Role for the caller. This can be a bitwise OR of the following values.

Value	Meaning
CA_ACCESS_READ 0x00000100	The caller can read the configuration information at the responder.
CA_ACCESS_ENROLL 0x00000200	The caller can request the response status for a particular certificate from the responder.
CA_ACCESS_ADMIN 0x00000001	The caller can update the configuration information at the responder.
0x00000000	The caller has no roles.

3.2.4.1.10 Ping (Opnum 12)

This method queries the Online Responder Service to find out whether it is running.

```
HRESULT Ping();
```

This method has no parameters.

If the Online Responder Service is running, the server **MUST** return success (0) when this method is invoked.

3.2.5 Timer Events

None.

3.2.6 Other Local Events

None.

4 Protocol Examples

An administrator needs to enable the responder to create OCSP responses for clients requesting revocation status for certificates issued by a CA called "CA1", which runs on a machine called "Server1".

CA1 is configured to issue certificates based on a certificate template called "OCSPResponseSigning".

This means that the administrator needs to create a new revocation configuration on the responder, configured for the CA certificate of CA1.

1. The client needs to query all the revocation configuration IDs currently configured on the responder to ensure that it does not overwrite an existing entry. The client queries the responder revocation configuration list using the [GetOCSPProperty](#) method, with *bstrEntryName* of "CAEntries".
2. The server returns the list of revocation configuration IDs currently on the server as the variant referenced by parameter *pEntryValue* (for each revocation configuration in [RevocationConfigurationList](#), there should be an element in the safearray referenced by *pArray* that contains the [BSTR](#) for the Unicode string value of the *RevocationConfigurationId*).
3. The client reads the list of revocation configuration IDs returned by the server and creates a unique *RevocationConfigurationId* (that is, not a duplicate of any existing entry).
4. The client then constructs a variant of type `VT_ARRAY|VT_VARIANT` whose *pArray* member points to a two-dimensional array. The two-dimensional array will have one element of the first dimension (that is, one row) for each revocation configuration property the administrator wishes to set. The array will have two elements of the second dimension (that is, columns) for each element of the first dimension: one containing a variant of type `VT_BSTR` whose **bstrVal** contains the name of a revocation configuration property, and one containing a variant with the value for that property. The property value variants are constructed as follows:
 1. CA Certificate property:
 1. **vt** member is `VT_ARRAY |VT_VARIANT`.
 2. *pArray* references a single dimension safearray with one element for each byte of the ASN1 DER encoded CA certificate for CA1.
 2. SigningFlags property:
 1. **vt** member is `VT_I4`.
 2. **IVal** contains the value whose hex representation is 0x0000025d. This means that the following Signing Flags are set (defined in section [3.2.4.1.3](#)):
 1. 0x01 – silently acquire private key
 2. 0x04 – auto-use renewed signing certificate
 3. 0x08 – signing certificate signed by CA certificate key
 4. 0x10 – automatically look for an OCSP cert
 5. 0x40 – responses include key hash of signing certificate

6. 0x200 – enroll for a signing certificate from CAConfig, using SigningCertificateTemplate
3. ProviderCLSID property:
 1. **vt** member is VT_BSTR.
 2. **bstrVal** contains the BSTR representation of the Unicode string representation of "{4956d17f-88fd-4198-b287-1e6e65883b19}".
4. Provider property:
 1. **vt** member is VT_ARRAY|VT_VARIANT.
 2. **pArray** points to another two-dimensional array with property name and property value pairs like those described for the containing variant array.
 - BaseCrlUrls property:
 1. **vt** member is VT_ARRAY|VT_BSTR.
 2. **pArray** points to a single dimension safearray, in which each element is a BSTR representation of the Unicode representation of a URI where the responder can contain a CRL published by CA1. In this example, the value "http://CA1.Server1.contoso.com/CRL/CA1.crl" is used.
5. SigningCertificateTemplate:
 1. **vt** member is VT_BSTR.
 2. **bstrVal** is the BSTR representation of the Unicode string representation of "OCSPResponseSigning" (the template name).
6. CAConfig:
 1. **vt** member is VT_BSTR.
 2. **bstrVal** is the BSTR representation of the Unicode string representation of "Server1\CA1", the CA configuration string.
5. The client calls the [SetCAConfigInformation](#) method on the server, passing the newly generated RevocationConfigurationId as the *bstrCAId* parameter, and a *pEntryValue* pointing to the variant constructed in step 4, containing configuration values for the new revocation configuration.
6. The server creates the new revocation configuration and returns S_OK.

5 Security

5.1 Security Considerations for Implementers

5.1.1 Strong Administrator Authentication

An administrator of the responder must authenticate strongly. This could be via a high-entropy password or some multiple-factor authentication method (such as a smart card). The administrator should use a login account that functions only for responder administration and not for any other function, because use of the same credentials on a vulnerable computer while performing some other task exposes the credentials to capture and misuse.

5.1.2 KDC Security

Because authentication of the administrator is by Kerberos, in this protocol, the key distribution center (KDC) must itself be kept secure—free from tampering and free from vulnerabilities that would allow privilege-elevation penetrations.

5.1.3 Administrator Console Security

The administrator's console (the applications used by the administrator to run the client side of this protocol and the operating system in which that functionality runs) must be kept secure from penetration that would allow an attacker to act as the administrator.

5.1.4 Administrator Credential Issuance

Because the administrator is identified as some name in a Kerberos domain, for the purpose of access control by the responder, the human procedures for assigning a name to the administrator, adding that name to some named group of administrators and adding that group name to the **access control list (ACL)** used by the responder, must be kept free from either penetration (for example, social engineering) or human mistake via common misspelling or unwarranted assumptions.

5.1.5 Practices when Using Cryptography

Any cryptographic protocol has security considerations dealing with key handling during cryptographic operations and key distribution. Although a public-key certificate is not a protocol by itself, it has most of the same security considerations of a cryptographic protocol in the sense that a public key certificate is a message from the CA to the responder a message addressed, in effect, "to whom it may concern". A cryptographic protocol that deals with the transmission or issuance or other use of a public key certificate therefore has security considerations in two areas: around the protocol itself and around the certificate and its use.

In addition, a certificate binds two or more pieces of information together. In the most common case, that would be a public key and a name. The name in such a certificate has security relevance, and there are security considerations around the use and provisioning of those names. In some certificate forms, there are attributes bound to either a name or a key, and there are security considerations around the use and provisioning of those attributes.

5.1.5.1 Keeping Information Secret

Any cryptographic key must be kept secret. One must also keep secret any function of a secret (such as a key schedule), because knowing such functions would reduce an attacker's work in cryptanalyzing the secret.

When a secret must be in the normal memory of a general purpose computer in order to be used, that secret should be erased (for example, replaced with a constant value, like 0) as soon as possible after use.

A secret may be kept in a specially protected memory where it can be used without being erased. Typically, one finds such memory in a Hardware Security Module (HSM). If an HSM is used, it should be compliant with [\[FIPS140\]](#), or the equivalent at a level consistent with the security requirements of the customer deploying the cryptographic protocol or the CA that uses the HSM.

5.1.5.2 Coding Practices

Any implementation of a protocol exposes code to inputs from attackers. Such code must be developed according to secure coding and development practices in order to avoid buffer overflows, denial of service attacks, escalation of privilege, and disclosure of information. For an introduction to these concepts, as well as secure development best practices and common errors, see [HOWARD].

5.1.5.3 Security Consideration Citations

Implementers of this protocol should take care to consider the following security considerations:

- A client or server should follow generally accepted principles of secure key management. For more information, see section 9 of [\[RFC3280\]](#). For an introduction to these generally accepted principles, see [\[CRYPTO\]](#) and [HOWARD].
- Clients and servers should validate cryptographic parameters prior to issuing or accepting certificates. For more information, see section 9 of [\[RFC2797\]](#).
- A client and server should validate and verify certificate path information identified in section 6 of [\[RFC3280\]](#). See section 9 of [\[RFC3280\]](#) for more information on the requirement for certificate path validation.
- A client and server should validate and verify the freshness of revocation information of all digital certificates prior to usage, trust, or encryption as identified in section 6.3 of [\[RFC3280\]](#). See section 9 of [\[RFC3280\]](#) for more information on the requirement for revocation freshness.
- A client or server should follow all security considerations in section 5 of [\[RFC2560\]](#).
- A client or server should follow all security considerations discussed throughout [\[RFC2315\]](#) and [\[RFC2986\]](#), because neither normative reference has a specific security section.
- A client and server should use an authenticated HTTP session between client and server to mitigate denial of service attacks. For more information on generic denial-of-service (DoS) mitigation techniques, see [HOWARD].

5.2 Index of Security Parameters

None.

6 Appendix A: Full IDL

For ease of implementation, the full **Interface Definition Language (IDL)** is provided, where "ms-oaut.idl" is the IDL found in [\[MS-OAUT\]](#) Appendix A.<17>

```
import "ms-oaut.idl";

typedef struct _CERTTRANSBLOB
{
    unsigned long        cb;
    [size_is(cb), unique] BYTE *pb;
} CERTTRANSBLOB;
// Interface IOCSAdminD

[
    object,
    uuid(784b693d-95f3-420b-8126-365c098659f2),
    helpstring("IOCSAdminD DCOM Interface"),
    pointer_default(unique)
]

interface IOCSAdminD: IUnknown
{

HRESULT GetOCSPProperty(
[in, ref] const BSTR bstrEntryName,
[out, ref] VARIANT* pEntryValue);

HRESULT SetOCSPProperty(
[in, ref] const BSTR bstrEntryName,
[in, ref] const VARIANT *pEntryValue);

HRESULT GetCAConfigInformation(
[in, ref] const BSTR bstrCAId,
[out, ref] VARIANT* pEntryValue);

HRESULT SetCAConfigInformation(
[in, ref] const BSTR bstrCAId,
[in, ref] const VARIANT *pEntryValue);

HRESULT GetSecurity(
[out, ref] CERTTRANSBLOB *pctbSD);

HRESULT SetSecurity(
[in, ref] CERTTRANSBLOB *pctbSD);

HRESULT GetSigningCertificates(
[in, ref] const VARIANT *pCAVar,
[out, ref] VARIANT* pSigningCertificates);

HRESULT GetHashAlgorithms(
[in, ref] const BSTR bstrCAId,
[out, ref] VARIANT* pHashAlgorithms);

HRESULT GetMyRoles(
[out]LONG *pdwRoles);
```



```
HRESULT Ping();
```

```
};
```

7 Appendix B: Product Behavior

The information in this specification is applicable to the following Microsoft products or supplemental software. References to product versions include released service packs:

- Windows Server 2008 operating system
- Windows Server 2008 R2 operating system
- Windows Server 2012 operating system
- Windows Server 2012 R2 operating system

Exceptions, if any, are noted below. If a service pack or Quick Fix Engineering (QFE) number appears with the product version, behavior changed in that service pack or QFE. The new behavior also applies to subsequent service packs of the product unless otherwise specified. If a product edition appears with the product version, behavior is different in that product edition.

Unless otherwise specified, any statement of optional behavior in this specification that is prescribed using the terms SHOULD or SHOULD NOT implies product behavior in accordance with the SHOULD or SHOULD NOT prescription. Unless otherwise specified, the term MAY implies that the product does not follow the prescription.

[<1> Section 3.2.1.2:](#) The name of the machine used in the Microsoft implementation is the fully qualified domain name (FQDN) (1) of the machine.

[<2> Section 3.2.1.2:](#) The names of the machines used in the Microsoft implementation are the FQDNs (1) of the machines.

[<3> Section 3.2.1.3:](#) A Microsoft Online Responder defines two permissions: Read and Administer. For responder security methods GetSecurity, SetSecurity, and GetMyRoles, the Microsoft Online Responder assigns permissions to principals (identified by the **ACE**) in the following manner.

Permission	Bit value	Meaning
Read	0x00000100	The caller can read the configuration information and properties of the responder.
Administer	0x00000001	The caller can update the configuration information and properties of the responder.

If a principal has Administer permission, Read permission is implied (does not need to be explicitly set).

The responder may enforce Online Responder security for each of the following methods by checking for the permissions identified in the following table.

Method name	Acceptable permissions
GetOCSPProperty	Read
SetOCSPProperty	Administrator
GetCAConfigInformation	Read
SetCAConfigInformation	Administrator

Method name	Acceptable permissions
GetSecurity	Read
SetSecurity	Administrator

The security descriptor on the responder controls which security principal can manage or read configuration information or request certificate status from the responder. Whenever a Read method on the responder is invoked, the responder checks this security descriptor to ensure that the calling entity has read access; if the entity doesn't have read access, the responder returns 0x80070005 as the error code. Whenever any Write method is invoked, the responder checks this security descriptor to ensure that the calling entity has manage access on the responder; if it does not, 0x80070005 is returned by the responder.

These methods require read access:

- [GetOCSPProperty](#)
- [GetCAConfigInformation](#)
- [GetSecurity](#)
- [GetSigningCertificates](#)
- [GetHashAlgorithms](#)
- [Ping](#)

These methods require manage access:

- [SetOCSPProperty](#)
- [SetCAConfigInformation](#)
- [SetSecurity](#)

The following method can be invoked by any caller:

- [GetMyRoles](#)

<4> [Section 3.2.1.3](#): A Microsoft Online Responder defines two permissions: Read and Administer. For responder security methods [GetSecurity](#), [SetSecurity](#), and [GetMyRoles](#), the Microsoft Online Responder assigns permissions to principals (identified by the ACE) in the following manner.

Permission	Bit value	Meaning
Read	0x00000100	The caller can read the configuration information and properties of the responder.
Administer	0x00000001	The caller can update the configuration information and properties of the responder.

If a principal has Administer permission, Read permission is implied (does not need to be explicitly set).

The responder may enforce Online Responder security for each of the following methods by checking for the permissions identified in the following table.

Method name	Acceptable permissions
GetOCSPProperty	Read
SetOCSPProperty	Administrator
GetCAConfigInformation	Read
SetCAConfigInformation	Administrator
GetSecurity	Read
SetSecurity	Administrator

The security descriptor on the responder controls which security principal can manage or read configuration information or request certificate status from the responder. Whenever a read method on the responder is invoked, the responder checks this security descriptor to ensure that the calling entity has read access; if the entity does not have read access, the responder returns 0x80070005 as the error code. Whenever any write method is invoked, the responder checks this security descriptor to ensure that the calling entity has manage access on the responder; if it does not, 0x80070005 is returned by the responder.

These methods require read access:

- [GetOCSPProperty](#)
- [GetCAConfigInformation](#)
- [GetSecurity](#)
- [GetSigningCertificates](#)
- [GetHashAlgorithms](#)
- [Ping](#)

These methods require manage access:

- [SetOCSPProperty](#)
- [SetCAConfigInformation](#)
- [SetSecurity](#)

The following method can be invoked by any caller:

- [GetMyRoles](#)

<5> [Section 3.2.4.1.1](#): For the Microsoft responder, this property has values between 5 and 9999.

<6> [Section 3.2.4.1.1](#): The Microsoft responder uses integer values between 0 and 6.

Value	Meaning
CERTLOG_MINIMAL 0x00000000	Log events for errors and warnings that occur on the responder.
CERTLOG_TERSE	Log errors, warnings, and informational events.

Value	Meaning
0x00000001 — 0x00000003	
CERTLOG_VERBOSE 0x00000004	Log extended events.
CERTLOG_EXHAUSTIVE 0x00000005 — 0x00000006	Throttling is removed for events that can be generated quickly, such as MSG_E_POSSIBLE_DENIAL_OF_SERVICE_ATTACK.

<7> [Section 3.2.4.1.1:](#) The Microsoft responder uses a value of 0xfffffe3 to indicate that debug tracing is enabled and 0 to indicate that it is not.

<8> [Section 3.2.4.1.1:](#) The Microsoft responder uses values between 1 and 24.

<9> [Section 3.2.4.1.1:](#) The Microsoft responder uses a default value of 20.

<10> [Section 3.2.4.1.1:](#) The Microsoft responder uses a value of 0xfffffe3 to indicate that debug tracing is enabled and 0 to indicate that it is not.

<11> [Section 3.2.4.1.1:](#) Windows does not return any vendor defined properties.

<12> [Section 3.2.4.1.2:](#) The type MUST match the value specified in section [3.2.4.1.1](#) if the server is a Windows responder. Otherwise, the responder might not function correctly.

<13> [Section 3.2.4.1.3:](#) The Microsoft responder uses the hash algorithms supported by the cryptographic provider specified in the CSPName property.

<14> [Section 3.2.4.1.3:](#) The Microsoft Online responder returns a value of {4956d17f-88fd-4198-b287-1e6e65883b19} for this property.

<15> [Section 3.2.4.1.5:](#) By default the Responder SD is as follows:

Owner: SID for Builtin\Administrators (S-1-5-32-544)

Group: SID for Builtin\Administrators (S-1-5-32-544)

2 ACE's with ACE_TYPE ACCESS_ALLOWED_ACE_TYPE (0x00):

Allow Builtin Admins to read and manage the responder.

Allow Network Service account to proxy requests.

2 ACE's with ACE_TYPE SYSTEM_AUDIT_ACE_TYPE (0x02):

Audit Success and Failure for everyone when they try to access for the 0xffff (any) access rights.

Audit Success and Failure for anonymous users when they try to access for the 0xffff access rights.

Within the ACCESS_MASK, the bit values have the following meanings:

Permission	Bit Value	Meaning
Read	0x00000100	Read the configuration information and properties of the responder.
Administer	0x00000001	Update the configuration information and properties of the responder.
Proxy requests	0x00000300	Proxy requests (if the responder is split into a front end and back end service).

<16> [Section 3.2.4.1.8](#): The Microsoft Online Responder returns the hash algorithms supported by the "Microsoft Strong Cryptographic Provider" CSP in the default list of hash algorithms.

<17> [Section 6](#): The Microsoft implementation of the OCSP admin interface has a CLSID whose value is { 0x6d5ad135, 0x1730, 0x4f19, { 0xa4, 0xeb, 0x3f, 0x78, 0xe7, 0xc9, 0x76, 0xbb}}.

8 Change Tracking

No table of changes is available. The document is either new or has had no changes since its last release.

9 Index

A

Abstract data model
[client](#) 12
[server](#) 12
[Applicability](#) 9

C

[Capability negotiation](#) 9
[Change tracking](#) 39
Client
[abstract data model](#) 12
[initialization](#) 12
[local events](#) 12
[message processing](#) 12
[sequencing rules](#) 12
[timer events](#) 12
[timers](#) 12
[Common data types](#) 11

D

Data model - abstract
[client](#) 12
[server](#) 12
[Data types - common - overview](#) 11

E

[Examples - overview](#) 28

F

[Fields - vendor-extensible](#) 9

G

[GetCAConfigInformation method](#) 20
[GetHashAlgorithms method](#) 26
[GetMyRoles method](#) 26
[GetOCSPProperty method](#) 16
[GetSecurity method](#) 24
[GetSigningCertificates method](#) 25
[Glossary](#) 6

I

[Implementer - security considerations](#) 30
[Index of security parameters](#) 31
Initialization
[client](#) 12
[server](#) 15
[Introduction](#) 6

L

Local events
[client](#) 12

[server](#) 27

M

Message processing
[client](#) 12
[server](#) 16
Messages
[common data types](#) 11
[overview](#) 10
[transport](#) 10

O

[Overview \(synopsis\)](#) 8

P

[Parameters - security index](#) 31
[Ping method](#) 27
[Preconditions](#) 9
[Prerequisites](#) 9
[Product behavior](#) 34

R

[Relationship to other protocols](#) 9

S

Security
[implementer considerations](#) 30
[parameter index](#) 31
Sequencing rules
[client](#) 12
[server](#) 16
Server
[abstract data model](#) 12
[initialization](#) 15
[local events](#) 27
[message processing](#) 16
[sequencing rules](#) 16
[timer events](#) 27
[timers](#) 15
[SetCAConfigInformation method](#) 24
[SetOCSPProperty method](#) 19
[SetSecurity method](#) 25
[Standards assignments](#) 9

T

Timer events
[client](#) 12
[server](#) 27
Timers
[client](#) 12
[server](#) 15
[Tracking changes](#) 39
[Transport](#) 10

V

[Vendor-extensible fields](#) 9

[Versioning](#) 9